

Список команд управления для интерактивных панелей Lumien серии ELN

Перечисленные ниже команды применяются для следующих моделей интерактивных панелей Lumien:

- LMP6502ELN
- LMP7502ELN
- LMP8602ELN
- LMP6504EL
- LMP7504EL
- LMP8604EL
- LMP9804EL

Настройки подключения RS232:

- Baud rate: 115200
- Data bit: 8bits
- Parity: None
- Stop bit: 1

Настройки подключения IP:

- IP-адрес: полученный интерактивной панелью
- Порт: 4660

Команда	HEX
SET_POWER_ON	6B303173413030310D (только для RS232)
SET_POWER_STANDBY	6B303173413030300D
SET_SOURCE_TO_HDMI	6B303173423030340D
SET_SOURCE_TO_HDMI1	6B303173423031340D
SET_SOURCE_TO_HDMI2	6B303173423032340D
SET_SOURCE_TO_VGA	6B303173423030360D
SET_SOURCE_TO_OPS	6B303173423030370D
SET_SOURCE_TO_TYPEC	6B303173423030430D
SET_SOURCE_TO_DP	6B303173423030390D
SET_SOURCE_TO_REAR_TYPEC	6B303173423030400D
SET_SOURCE_TO_ANDROID	6B303173423030410D
SET_CONTRAST	6B303173433X3X3X0D
SET_BRIGHTNESS	6B303173443X3X3X0D
SET_SHARPNESS	6B303173453X3X3X0D
SET_SATURATION	6B303173463X3X3X0D
SET_COLOR_MODE_NORMAL	6B303173483030300D
SET_COLOR_MODE_WARM	6B303173483030310D
SET_COLOR_MODE_COLD	6B303173483030320D
SET_COLOR_MODE_USER	6B303173483030330D
SET_BASS	6B3031734A3X3X3X0D
SET_TREBLE	6B3031734B3X3X3X0D
SET_BALANCE	6B3031734C3X3X3X0D
SET_LANGUAGE English	6B3031734E3030300D
SET_LANGUAGE French	6B3031734E3030310D
SET_LANGUAGE Spanish	6B3031734E3030320D
SET_LANGUAGE Traditional Chinese	6B3031734E3030330D
SET_LANGUAGE Simple Chinese	6B3031734E3030340D
SET_LANGUAGE Portuguese	6B3031734E3030350D
SET_LANGUAGE German	6B3031734E3030360D
SET_LANGUAGE Dutch	6B3031734E3030370D
SET_LANGUAGE Polish	6B3031734E3030380D
SET_LANGUAGE Russia	6B3031734E3030390D

SET_LANGUAGE_Czech	6B3031734E3031300D
SET_LANGUAGE_Danish	6B3031734E3031310D
SET_LANGUAGE_Swedish	6B3031734E3031320D
SET_LANGUAGE_Italian	6B3031734E3031330D
SET_LANGUAGE_Romanian	6B3031734E3031340D
SET_LANGUAGE_Norwegian	6B3031734E3031350D
SET_LANGUAGE_Finnish	6B3031734E3031360D
SET_LANGUAGE_Greek	6B3031734E3031370D
SET_LANGUAGE_Turkish	6B3031734E3031380D
SET_LANGUAGE_Arabic	6B3031734E3031390D
SET_LANGUAGE_Japanese	6B3031734E3032300D
SET_LANGUAGE_Korean	6B3031734E3032320D
SET_VOLUME	6B303173503X3X3X0D
SET_VOLUME_DOWN	6B303173503230300D
SET_VOLUME_UP	6B303173503230310D
SET_MUTE_OFF	6B303173513030300D
SET_MUTE_ON	6B303173513030310D
SET_NUMBER	6B303173533x3x3x0D
KEY_PAD_UP	6B3031735B3030300D
KEY_PAD_DOWN	6B3031735B3030310D
KEY_PAD_LEFT	6B3031735B3030320D
KEY_PAD_RIGHT	6B3031735B3030330D
KEY_PAD_ENTER	6B3031735B3030340D
KEY_PAD_INPUT	6B3031735B3030350D
KEY_PAD_EXIT	6B3031735B3030370D
SET_REMOTE_CONTROL_LOCK	6B303173563030300D
SET_REMOTE_CONTROL_UNLOCK	6B303173563030310D
SET_DATE_YEAR	6B30317358593x3x0D
SET_DATE_MONTH	6B303173584D3x3x0D
SET_DATE_DAY	6B30317358443x3x0D
SET_DATE_HOUR	6B30317359483x3x0D
SET_DATE_MIN	6B303173594D3x3x0D
SET_DATE_SEC	6B30317359533x3x0D
SET_RESET_DEFAULT	6B3031735A3030300D
SET_TOUCH_LOCK	6B3031735C3030310D
GET_CONTRAST	6B303167613030300D
GET_BRIGHTNESS	6B303167623030300D
GET_SHARPNESS	6B303167633030300D
GET_SATURATION	6B303167643030300D
GET_VOLUME	6B303167663030300D
GET_MUTE	6B303167673030300D
GET_CURRENT_INPUT_SOURCE	6B303167683030300D
GET_REMOTE_CONTROL_LOCK	6B3031676A3030300D
GET_OPERATION_TIME	6B3031676F3030300D
GET_DATE_YEAR	6B303167704830300D
GET_DATE_MONTH	6B303167704D30300D
GET_DATE_DAY	6B303167704430300D
GET_DATE_HOUR	6B303167714830300D
GET_DATE_MIN	6B303167714D30300D
GET_DATE_SEC	6B303167715330300D
GET_DEVICE_NAME	6B303167723030300D
GET_MAC_ADDR	6B303167733030300D
GET_TOUCH_LOCK	6B303167753030300D